

DAC Box E

Digital-to-analogue converter

- 24bit / 192kHz D/A conversion
- Co-axial (RCA) & optical (Toslink) S/PDIF input
- SMD circuitry
- Special low noise components
- Internal metal shielding
- Small size allows installation close to source
- Gold plated RCA connection sockets
- Outboard power supply included
- Black or White casing

Technical data

Line-level output	1 pair RCA/phono sockets
Output voltage	0,7Vrms
Digital inputs	1x coaxial (S/PDIF), 1x optical (TOSlink®)
D/A converter	Texas Instruments TLV320DAC23 Cirrus Logic CS4344. 24Bit/192kHz
Supported audio format:	PCM (LPCM) (Stereo only, no support for multi-channel formats)
Sampling rates	
Optical and coaxial input	44,1kHz, 48kHz, 96kHz and 192kHz (coaxial only)
Outboard power supply	18V/500mA DC
Power consumption	200mA DC, <1W in standby
Dimensions W x H x D (D with sockets)	120 x 32 x 100 (106)mm
Weight	250g without power supply

HI-RES AUDIO
BY PRO-JECT AUDIO SYSTEMS



SRP
99,00 €

DAC Box E: Pure listening pleasure for digital sources at an absolute bargain price!

The entry-level DAC Box E is an excellent D/A converter for digital sound sources using optical and coaxial connections. Despite the low price, it sounds outstanding and supports HD music data up to 24/192kHz. DAC Box E uses high quality components like precision D/A converter chips and a low noise output stage. It will act as a perfect upgrade for any digital stereo audio source, especially for best-buy CD-players, Bluray or DVD players with CD playback, set-top boxes etc!

The whole audio circuitry design is perfectly linear with low output impedance to avoid any negative interference with cables or pre-amps. Its class-leading audio performance makes DAC Box E an outstanding low-cost audio bargain!



- Back view >
- ◇ RCA stereo
 - ◇ Co-axial In
 - ◇ Toslink In
 - ◇ Power
- < black version

